



Frequency Band : 2.4 GHz ~ 2.5 GHz  
Modulation : FSK  
Bit Rate : 4800 ~ 14400 Bps  
Output Power : +4.5dbm  
Impedance : 50 ohms  
Substrate material : Rogers RO4003C  
PCB thickness : 0.508 mm  
Dielectric constant : 3.3  
Module Specifications :  
Base band transmitter :  
Frequency band : 2.4 ~ 2.5 GHz  
Gain : 26 dB  
Noise figure : 2.5 dB  
Input p1 dB : -25dBm  
Power divider :  
&nbsp;   Type : 2 way, Wilkinson  
Frequency band : 2.4 ~ 2.5 GHz  
Return loss : 14 dB  
Insertion loss : 0.5 dB  
&nbsp;   Band pass filter (2.4 GHz) :  
Type : Edge-coupled  
Center frequency : 2.4 GHz  
Return loss : 10 dB  
Insertion loss : 7.0 dB  
Band pass filter (2.5 GHz) :  
Type : Edge-coupled  
Center frequency : 2.5 GHz  
Return loss : 10 dB  
Insertion loss : 7.0 dB  
R F amplifier :  
Frequency band : 2.4 ~ 2.5 GHz  
Gain : 15 dB  
Input : -5dBm  
Antenna & Receiving :  
&nbsp;   Type : YAGI (PCB type)  
Center frequency : 2.45 GHz  
Gain : 9 dBi  
VSWR : 1.5 : 1  
Components Device :  
&nbsp;   FSK Modulator : 1 ea  
FSK Demodulator : 1 ea  
R F &nbsp;   Amplifier : 2 ea  
Detector : 2 ea  
Band Pass Filter 2.4 GHz : 1 ea  
Band Pass Filter 2.5 GHz : 1 ea  
Power Divider : 1 ea  
Low Noise Amplifier : 1 ea  
YAGI antenna : 2 ea  
DC Power Adaptor (1.2V / 1.5A) : 2 ea  
DC Power Cable : 2 ea  
RS &nbsp;   232C &nbsp;   Cable : 2 ea  
R F Cable : 3 ea  
Carrying Bag : 1 ea

Antenna Cable : 2 ea  
Antenna Supporter : 2 set  
SMA &nbsp;Adaptor : 6 ea  
50 Ohm Terminator : 1 ea  
Software program : 1 ea  
Answer sheet in CD : 1 ea  
Program CD : 1 ea  
&nbsp;

## Naugra Export

**Website:** www.naugraexport.com, **Email:** sales@naugraexport.com

**Address:** 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India, **Phone:** +91-0171-2643080, 2601773