

**Product Name :**

Stereo Tape Recorder Trainer & Lab Training Kit for Vocational Training and Didactic Labs

**Product Code :**

CON-025-NE

**Description :**

Equipment for Education, Engineering and Vocational Training - Stereo Tape Recorder Trainer & Lab Training Kit - Stereo Tape Recorder Trainer is ideal equipment to teach the operation of stereo recording and stereo cassette playing function. The comprehensive study of Tape record and Mechanism unit technique is described in the operating manual. One of the main features of this trainer is fault simulation. The fault created in the trainer in no way damages the trainer.

**Technical Specifications**

Amplifier Type : Class B amplifier

Audio Power Output : 14 W (7 W × 2 channels )

Frequency Response : 100 Hz to 8 KHz

Tape Speed : 4.75 cm / sec

Erase Head : Fix magnet

RP Head : YBBT 62 (Stereo)

Mechanism : R X 39

Motor : CCW 12 V DC

**Circuit Block :**

Pre amplifier CH-L & CH-R

Bass - Treble CH-L & CH-R

Output amplifier CH-L & CH-R

Equalization CH-L & CH-R

Output level indicator section

Power supply section

**Panel Control :**

Volume CH-L & CH-R

Bass CH-L & CH-R

Treble CH-L & CH-R

Mechanism Control : Record, Play, Reverse, Forward, Stop, Pause

Recording Facility : Condenser Mic and EP socket for feeding external signal

PCB Size (mm) : 260 × 230

No. of faults : 15

No. of Test point : 42

Power Supply : 220 V ±10 %, 50 Hz / 60 Hz on request

Power Consumption : 8.17 W (approx.)

Compact design  
Fault creation and diagnosis  
42 Test Points  
More than 15 faults can be demonstrated on this trainer  
No soldering and de-soldering is required to simulate faults  
The main IC's are provided on socket to provide a facility to check similar IC' and also to create the faults by inserting faulty IC's in the sockets  
Test points detail with typical voltage and wave forms are provided in the manual  
In built power supply  
Two identical mono channels clubbed together to obtain stereo effect through stereo head Both internal and external recording facility available  
Recording process understood through LED indicator present in equalization section  
8P-2W R/P switch mechanism planed widely through 16 nos 1P-2W toggle switches  
Separate bass/treble section to understand the effect of low frequency as well as high frequency signal

## Naugra Export

**Website:** [www.naugraexport.com](http://www.naugraexport.com), **Email:** [sales@naugraexport.com](mailto:sales@naugraexport.com)

**Address:** 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India, **Phone:** +91-0171-2643080, 2601773